

ECS DMX A/B Switch Specification

	12 way DMX A/B Switch	8 way DMX A/B Switch
		
Connectivity		
DMX Input	24x Neutrik 5 pin XLR Male (Front)	16x Neutrik 5 pin XLR Male (Front)
DMX Output	12x Neutrik 5 pin Female (Rear)	8x Neutrik 5 pin XLR Female (Rear)
Power	1x Neutrik PowerCON True1 In/Out	1x Neutrik PowerCON True1 In/Out
Features		
Power Indicator Light	On front panel	On front panel
Response on power loss	Default to pass 'A' inputs	Default to pass 'A' inputs
RDM	RDM passthrough	RDM passthrough
Switch	Robust positive click A/B Switch	Robust positive click A/B Switch
Chassis	Tour friendly steel chassis	Tour friendly steel chassis
Power		
Power Input	86-264V AC; 3A; 47-63Hz	86-264V AC; 3A; 47-63Hz
Power Through	Max 15A	Max 15A
Power Consumption	86-264V AC, 0.2-0.1A, 47-63Hz	86-264V AC, 0.2-0.1A, 47-63Hz
Fuse	3A	3A
Physical		
Dimension (WxDxH)	484 x 200 x 89 mm	484 x 200 x 89 mm
Weight	3.35kg	3.25kg
In Packaging (WxDxH)	593 x 284 x 167 mm	593 x 284 x 167 mm
What's in the box	1x ECS 12 way DMX A/B Switch 1x PowerCon True1	1x ECS 8 way DMX A/B Switch 1x PowerCon True1
Approvals		
Certifications	CE*, RoHS*	CE*, RoHS*
Standards	DMX 512-A, RDM	DMX 512-A, RDM